

ER-5900

DUAL CHANNEL TRUE DIVERSITY WIRELESS MICROPHONE SYSTEM



ER-5900 series is a dual-channel true diversity wireless microphone. True diversity receiving mode is more stable, with AFS function, eliminating the reception drop out problem. The frequency response is wide, the sound quality is rich and full, with strong vocal expression. cardioid directional pickup, high sensitivity, while reducing environmental noise. The tone is high fidelity. It is suitable for karaoke, bars, night clubs, KTV and other entertainment venues.

Key Features



AFS(Automatic Frequency Selection)

- AFS Automatic frequency selection, Press the [AFS] (Auto Frequency Selection) button 3S and the receiver will auto-scan and lock on to an open, interference-free frequency .



Anti-Interference

- Adopt true diversity FM super-heterodyne reception to ensure the stability of the received RF signal and the anti-interference of the receiver itself; the operating frequency range is from 521.25MHz to 936.85MHz .



Classic Audio Companding Circuit

- Matching the Relacart's classic audio companding circuit to minimize the noise from the transmission of radio waves, and to ensure the maximum pickup effect of the product in use.



Intelligent Design

- The handheld microphone adopts the latest auto-mute, auto drop-to-mute, auto-off function. when the microphone is put horizontal or less than 45 degree for 5 sec, the microphone will be auto-mute. When the microphone is static for 10 mins, the microphone will be auto-off . When drop down, the microphone will be auto-mute. Intelligent electricity-saving, humanized application.
- The receiver comes with the electronic volume adjustment, the adjustment range is -6dB to +18dB, +3dB step.
- The receiver can display the battery level of the transmitter and can change according to the battery level of the transmitter.



Reliable Signal

- The BNC antenna can be connected to the coaxial antenna and the extended antenna, and provides the antenna power supply voltage.
- It can be connected to the Relacart classic Antenna distribution system, expand the multi-device, enhance the receiving distance and improve the signal stability.



IR Infrared

- With [IR] infrared automatic frequency matching function, press the [SYNC] button, the transmitter can automatically and accurately lock the working frequency of the receiver.



Generality

- 134MHz wideband transmitter, four different frequency band receivers can be used interchangeably, which greatly facilitates KTV debugging and management.
- Channel group mode is selected, and 50 channel groups in each frequency band provide user selection.

Product Specification



ER-5900

Dual Channel Wireless Receiver

- EIA Standard Rack 1U metal rack receiver chassis.
- Bright LCD display can simultaneously display the working channel or frequency, RF & AF signal status, transmitter battery consumption as well as mute level.

Tuning Bandwidth:	521.25MHz~936.85MHz
Receiving Mode:	FM Superheterodyne true diversity reception
RF Sensitivity:	5dBμV, S/N>60dB at 25 deviation
Squelch:	10dB to 40dB, 5dB step
Frequency Sync:	IR Sync
Maximum Output Level:	Maximum output + 11dBV
Adjustment Range of Audio Output Level:	-6dB to +18dB,3dB step
Power Requirements:	DC12V/1A
Current Consumption:	DV12V, 330mA
Overall Dimensions(mm):	410(W)×43(H)×206(D)
Net Weight:	1.8Kg



EH-6200

Wireless Handheld Microphone

- It adopts new alloy material and new technology electroplating coating, which is resistant to falling and durable, not easy to fade, and remains as good as new after long-term use. It uses a left-right toggle switch design, which is easy to operate. The switch has undergone 10,000 tests, with high durability and low loss. The wireless microphone is equipped with an LED display, which can show the channel group, battery level and frequency. The tail cover adopts an anti-falling design. It is suitable for various occasions such as speeches, singing performances and KTV.

Switching Bandwidth:	521.25MHz-936.85MHz
Oscillation:	PLL synthesized
RF Output Power:	5mW/30mW
Carrier Deviation:	0.5KHz
Harmonic Radiation:	≤45dB
Modulation:	FM
Nominal/ Peak deviation:	±45KHz
Max. Input Level:	Maximum input - 11dBv
Frequency Set-Up:	IR Sync
Power Requirements:	2X AA 1.5V batteries
Battery Life:	>8 hours
Dimensions(mm):	50(Φ) × 260(L)
Net Weight (without battery):	About 330g



ET-50

Wireless Bodypack Transmitter

- Bodypack-style wireless microphone, simple design, lightweight and practical engineering materials, durable, multi-function LCD display, built-in input selector switch, can be used to facilitate the instrument.
- The standard mini XLR microphone interface is suitable for a variety of well-known headset and clip microphones on the market. It is suitable for applications such as speech and singing.

Carrier Frequency Range:	521.25MHz~936.85MHz
Oscillation:	PLL Synthesized
Harmonic Radiation:	≤50dBm
Bandwidth:	134MHz (It depends on the region)
Max. Deviation Range:	±45KHz
Input Connector:	4-pin mini-XLR connector
RF Output Power:	20mW/2mW
Battery:	AA×2
Current Consumption:	110mA(Typical)
Battery Current/ Life:	Approximately 11 hours
Dimension(mm):	84(H)×66(W)×23(D)
Weight:	155g (w/o battery)