

MIXX 16 | DIGITAL MIXER



Description

MIXX16 Digital Mixer is a 16 inputs and 8 output digital wireless control mixer, is a new mixer through the tablet computer application control, can support all iOS, Windows 8 tablet and Android tablet. Using Wi-Fi to connect, anywhere in the wireless network within the scope of control. With 16 channels of broadcasting quality microphone amplifier (including 4 modular jack), main and aux outs. Adopt high performance 40 bit floating-point digital signal processor, 24 bit AD/DA converter. Built-in effects processor, compression and limiter, gate plug-ins, parametric equalizer Wireless control mode makes you can walk between the stage and the crowd. It is 16-channel digital mixer that with the iPad and tablet computer touch.

Product Specification

Sample Rate:	24bit, 48kHz
Frequency Respond :	20 Hz to 20 kHz +0/-1 dB
System Delay:	1.5 ms
T.H.D. :	<0.005%
Noise-Mic input to main output:	-72 dBv Single channel-Max fader(A weighted) -90dBv Single channel-Min fader (A weighted)
Input crosstalk (adjacent channel):	<-120 dB @1 kHz
S/N:	93dB Single channel-Max fader(A weighted)
Dynamic Range:	110dB Single channel-Max fader(A weighted)
CMR:	>70 dB @1 kHz
Input Impedance:	30 kΩ (1/4")
Gain:	0 to 60 dB (XLR) ; -20 to 40 dB (1/4")
Output Impedance:	600Ω (XLR Balance)
Max Output Level:	+21 dBu (XLR Balance)
Power Supply:	DC 12V-15V (3.5A)
Dimension(mm):	359 (L) x 85.5 (H) x 411 (D)
Weight:	Approximately 4.2kg