

MIXX8.6 | LIVE STREAMING LOOPBACK AUDIO USB MIXER



Compatible with
Relacart
Mi.Audio app



Description

MIXX8.6 digital mixer designed with 8 inputs and 6 outputs. Built-in digital audio processing functions, such as effect, EQ, compressor, etc. And it is equipped with a USB interface, which can transmit audio by mobile phones and computers. It has 16 types of digital reverb effects, which can be easily adjusted for various occasions with the encoder. It has a simple and exquisite appearance, with reasonable layout of function buttons, suitable for various small-scale performances, conferences, speeches, KTV, live streaming, and other occasions.

Product Specification

Sample Rate:	24bit, 48kHz
Frequency Response:	20 Hz to 20 kHz +0/-1 dB
T.H.D. :	<0.1%
Signal to Noise Ratio:	90 dB Single channel max fader (A weighted)
Dynamic Range:	100dB Single channel max fader (A weighted)
Common Mode Rejection Ratio :	>70 dB @1 kHz
MIC Input Impedance:	3.3k Ω (XLR Balance); 1.8 k Ω (1/4")
LINE Input Impedance:	10K Ω (1/4")
Output Impedance:	150 Ω
Gain:	0 to 60 dB (XLR)
FOOT SW :	REVERB ON/OFF
Phantom Power Supply:	+48V
USB Audio:	2IN/2OUT compliant with USB audio class 2.0
Power Supply:	DC 5V (1A)
Power Consumption:	Up to 5W
Dimensions(mm):	260(L)×230(H)×89(D)