

Product Specification

CR-2R

Wireless Bodypack
Receiver

Frequency Range:	470~960MHz
Receiving Mode:	Superheterodyne
Image Rejection:	45dBm
RF Sensitivity:	When input 10dBu, S / N ≥45dB
Squelch Adjustment:	Built-in setting parameters
Frequency Synchronization:	Manual key setting or infrared transmission
Maximum Output Level:	LINE : 0.5Vpp Phone : 1Vpp
Adjustment Range of Audio Output Level:	9 levels adjustable, attenuation adjustment, every 2dB step
Output Impedance	400Ω
Headphone Monitor Output:	Yes
Power Requirements:	AA 1.5V x 2
Current Consumption:	3V 160mA
Battery Life:	≤7 hours
Overall Dimensions (mm):	95×65×23
Net Weight:	110g(without battery)

Frequency Range:	470~960MHz
Oscillation:	PLL synthesized
RF Output Power:	13.5dBm
Carrier Deviation:	0.005%
Harmonic Radiation: :	-32dBm
Modulation:	FSK
Nominal/ Peak deviation:	± 65KHz
Max. Input Level:	250mV
Impedance:	2.2KΩ
Gain Adjustment Range:	4 levels of adjustable settings, every 3dB step
Frequency Set-Up:	Manual key setting or infrared transmission
Power Requirements:	AA 1.5V x 2
Current Consumption:	Battery powered:130mA
Battery Life:	≤11 hours
Overall Dimensions (mm):	95×65×23
Net Weight:	100g(without battery)

CB-2

Wireless Bodypack
Transmitter

Frequency Range:	470~960MHz
Oscillation:	PLL synthesized
RF Output Power:	13.5dBm
Carrier Deviation :	0.005%
Harmonic Radiation: :	-32dBm
Modulation:	FSK
Nominal/ Peak deviation:	± 65KHz
Max. Input Level:	250mV
Impedance:	2.2KΩ
Gain Adjustment Range:	4 levels of adjustable settings, every 3dB step
Frequency Set-Up :	Manual key setting or infrared transmission
Power Requirements:	AA 1.5V x 2
Current Consumption:	Battery powered:130mA
Battery Life:	≤11 hours
Overall Dimensions (mm):	110×42×42
Net Weight:	125g(without battery)

CP-2

Wireless Plug-on
Transmitter

Key Features



High Fidelity

- UHF dual channels wireless transmission, providing high-fidelity audio source



IR Infrared

- The infrared is automatically SYNC and locked to the selected application frequency.



Anti-Interference

- Multiple switchable frequency or use AFS function to achieve operation without environmental interference
- The transmit power is adjustable



Widely Compatible

- Widely compatible with smart phones, digital SLR cameras, camcorders, voice recorders, and personal computers;



Real-time Monitoring

- Output volume and monitor headphone volume can be adjusted independently
- The transmitter supports Mic and Line interfaces, volume adjustment, RF output power adjustment and so on. The receiver supports headphone and output volume adjustment, with AFS function. Working range is about 60 meters.



DSP Digital Audio Companding

- DSP digital audio companding, using 48KHz audio sampling rate, to minimize noise in the wireless transmission system



Convenient Design

- Use OLED display to display corresponding product information, brightness can be adjusted, and support Chinese and English language selection
- The receiver and transmitter are powered by two AA batteries

A highly cost-effective dual channel UHF wireless microphone system that is compatible with smart phones (3.5mm interface), digital / SLR cameras, camcorders, recorders, tablet computers and other devices to help pick up high-fidelity audio. This product is suitable for interviews, Micro movie recording or business presentations. The main feature is that both the transmitter and receiver use high-brightness OLED displays to display corresponding product information and support Chinese and English language selection. The infrared is automatically SYNC and locked to the selected application frequency. The transmitter supports Mic and Line interfaces, volume adjustment, RF output power adjustment and so on. The receiver supports headphone and output volume adjustment, with AFS function. Working range is about 60 meters.