

TGS-6R | WIRELESS TOUR GUIDE MICROPHONE SYSTEM RECEIVER



Description

Relacart TGS-6 Wireless Tour Guide Microphone System adopts UHF high-fidelity audio transmission technology to ensure stable use in various indoor and outdoor environments, and output high-quality sound, DSP digital audio companding processing can greatly reduce the noise of the wireless transmission. The innovative magnetic suction and soft rubber design is convenient for users to use, and can be attached to the collar, freeing hands to speak easily.

This wireless tour guide system allows visitors to stay connected to the guide's commentary while exploring freely. This system is ideal for tourism guide, factory tours, church activities, school meetings and more.

Product Specification

Receiving Bandwidth :	521.25MHz-936.85MHz
Receiving Method :	Superheterodyne
Image Rejection :	45dBm
RF Sensitivity :	When inputting 10dBu, S/N ≥ 45dB
SQ Adjustment :	Built-in setting parameters
Frequency Synchronization Method :	Manual key setting
Maximum Output level (analog) :	0.7Vpp
Output level adjustment range :	3-level adjustable, attenuated adjustment, every 3dB step
Audio Output:	3.5MM TS Jack
Power Supply Mode :	Built-in 3.7V 450mA lithium battery power supply
Normal Working Current :	100mA
Battery Life :	≥ 4 hours when the battery is fully charged
Dimensions(mm) :	67(H) × 32(W) × 13.5(D)
Net Weight :	31.5g