

TGS-6T | WIRELESS TOUR GUIDE MICROPHONE SYSTEM TRANSMITTER



Description

Relacart TGS-6 Wireless Tour Guide Microphone System adopts UHF high-fidelity audio transmission technology to ensure stable use in various indoor and outdoor environments, and output high-quality sound, DSP digital audio companding processing can greatly reduce the noise of the wireless transmission. The innovative magnetic suction and soft rubber design is convenient for users to use, and can be attached to the collar, freeing hands to speak easily.

The transmitter has a built-in omnidirectional condenser microphone and also supports external microphones with a 3.5mm jack. The receiver supports TS jack headphone output. The guide wears the transmitter, and tourists can move freely within a 20-meter range.

This wireless tour guide system allows visitors to stay connected to the guide's commentary while exploring freely. This system is ideal for tourism guide, factory tours, church activities, school meetings and more.

Product Specification

Carrier Bandwidth :	521.25MHz-936.85MHz
Oscillation Mode :	PLL frequency synthesis
Transmit Power :	13.5dBm
Carrier Deviation :	0.005%
Harmonic Radiation :	-32dBm
Modulation Method :	FM
Nominal/Max. Deviation Range :	± 65KHz
Maximum Input level :	250mV
Input gain Adjustment :	3 levels adjustable
Input Impedance :	2.2KΩ
Frequency Setting :	manual button to set frequency
Power Supply Mode :	built-in lithium battery or TYPE-C 5V power supply
Normal Working Current :	100mA
Battery Life :	≥ 4 hours when the battery is fully charged
Dimensions(mm) :	67(H) × 32(W) × 13.5(D)
Net Weight :	31.5g