

250mm



M-C37
User Manual


Features

Relacart M-C37 condenser microphone module, The highly consistent cardioid pickup can achieve maximum sound insulation, minimize off-axis interference, and high sound pressure. The tolerable and suitable frequency response curve accurately restores all kinds of sounds, whether you are speaking or singing, it can meet your needs and give you the true sound reproduction.


M-C37 is a high-quality vocal microphone module. It adopts a cardioid condenser microphone core design. The advanced microphone head shockproof system can absorb mechanical vibration and reduce the touch noise to a minimum. The three-stage blowproof prevention net cover can be maximized. Minimize the "poof" sound and noise of breathing, compatible with Relacart HR series handheld wireless microphones as well as Sennheiser® handheld wireless microphones.

Sennheiser® is a registered trademark of Sennheiser electronic GmbH & Co. KG and has no affiliation with this product.

Frequency Response



Polar Pattern



Product Specification

Adaptation: Relacart HR series wireless handheld microphones
Sennheiser® wireless handheld microphones

Type: Condenser

Directivity: Cardioid

Frequency Response: 100~18000Hz

Flexibility: -43dB @ 1V/Pa

Max SPL: 145dB @ 1%

Dimension: ϕ 54mm x 76mm

Weight: About 155g

Support

If you have any inquiries or questions about your Relacart product, please contact us directly:

<http://www.relacart.cn/contact>

Precautions

Aim the microphone at the sound source you want to record (such as a singer or instrument) and keep it away from other sound sources.
Get as close as possible to the sound source you want to record.
If you want more low frequency response, move the mic closer to the source.
Use only one microphone to pick up a single sound source.
Keep the distance between microphones at least three times the distance between each microphone and its sound source.
Position the microphone as far away from reflective surfaces as possible.
When using the microphone outdoors, a windscreens should be added.
Do not cover any part of the microphone filter with your hands as this will affect microphone performance.
Do not cover any part of the microphone filter with your hands as this will affect microphone performance.

This product complies with the standards listed in the declaration of conformity. Technical data are subject to change without notice.



70mm

250mm



Most Sincerely,
Your relacart Team
您最真诚的 relacart 团队


特性

Relacart M-C37 电容麦克风模组，高一致的心形拾音可以实现最大限度隔音，将离轴干扰降至最低，高声压耐受和适合的频率响应曲线准确还原各种声音，无论演讲或者演唱都能满足您的需求，给您真实的声音还原。


M-C37 是一款优质的人声麦克风模组，采用心型指向电容咪芯设计，先进的话筒头防震系统能够吸收机械振动，并将触摸噪声降低到最小，三级防喷网罩可最大限度地降低呼吸的“噗”声和噪声。适配于 Relacart HR 系列手持式无线麦克风，同时兼容 Sennheiser® 部分手持式无线麦克风。

Sennheiser® 是森海塞尔电子有限公司的注册商标，与本产品无关。

频率响应



极性响应



技术规格

适配: Relacart HR 系列无线麦克风
Sennheiser® 无线麦克风

类型: 电容式

指向: 心形

频率响应: 100~18000Hz

灵敏度: -43dB @ 1V/Pa

最大声压级 SPL: 145dB @ 1%

尺寸: ϕ 54mm x 76mm

重量: 约155g

支持

如果您的relacart产品出现任何问题或有有任何疑问，请直接与我们联系：

<http://www.relacart.cn/contact>

注意事项

话筒要对准要录制的声源（例如演唱者或乐器），远离其他声源。
尽可能地靠近要录制声源。
如果想获得更多的低频响应，可将话筒进一步靠近音源。
只使用一个话筒来拾取单个声源。
保持话筒之间的距离，使其至少三倍于每个话筒与其声源之间的距离。
将话筒放置在尽可能远离反射表面的位置。
在户外使用话筒时，应添加一个防风罩。
切勿用手遮盖住话筒滤网的任何部位，因为这会影响话筒性能。
话筒钢丝网罩内的海棉滤网需不定期清洁或更换，因为异物会影响话筒性能。

本产品符合《合格声明》所列标准。
技术资料如有更改，恕不另行通知。



70mm

双面：250 x 70 mm，100克书写纸
红色框：说明书尺寸
红色虚线：折叠位置（风琴折法）