



Relacart Mikit series is a portable stereo digital audio converter. It can be connected to a mobile device through the USB-C interface. Use with MI.AUDIO application software. Built-in DSP processor, you can set the input gain, monitor volume, high-pass filter, limiter, equalizer, mono/stereo switch, preset and other functions. It is widely used in recording, video recording, online communication, etc. Compatible with iOS (Only for Mikit-i version), Android, Windows, Mac (Only for Mikit-i version), plug and play.

Product Specification



Model:	Mikit-c (USB-C) Mikit-a (USB-C) (not yet available) Mikit-i (USB-C) (not yet available)
Gain Adjustment Range:	0 ~ +35dB
Frequency Response:	20Hz ~ 20KHz
Sampling Rate:	48K
Equalizer:	5-band graphic equalization / 5-band parametric equalization, switching applications
High Pass Filter:	75Hz / 150Hz
Limiter:	High / Medium / Low three-level adjustment
Case:	All metal structure, light and small, easy to carry
Dimensions(mm):	Mikit-c: 47(H)×47(W)×13(D) Mikit-a: 210(H)×47(W)×13(D) Mikit-i: 210(H)×47(W)×13(D)
Weight:	Mikit-c: 30g Mikit-a: 40g Mikit-i: 40g

Mikit.c/Mikit.a/Mikit.i

Mobile Interview Kit

Key Features

- 3.5mm Dual Microphone Input
- Mono/Stereo Mode Switch
- 3.5mm Monitor Outputs
- Lightweight
- APP application
• Pairs with relacart MI.AUDIO App.
- Widely Compatible
- Smart Chip
- Customizable Sound Quality
- Dual 3.5mm TRS Connection



MI.AUDIO APP