



Podcast⁺ is a podcast production studio specially designed for live streaming app, which collects the live application functions such as mixing, sound effects, and effects. Can connect 2 mobile phones or PC at the same time to transmit to live broadcast equipment through digital audio. Its design is light and easy to carry, the panel layout is simple, and the function distinction is clear and easy to understand. This device is powered by a USB-C interface 5V/1A and supports power from a suitable mobile phone charger or power bank. Podcast+ is suitable for live broadcast, recording, Karaoke and other functions of mobile phones, tablets and PC, etc.

Product Specification



Sample Rates:	24 - bit, 48 KHz
Frequency Response:	20Hz to 20 KHz
System Delay:	1.5ms
T.H.D:	< 0.05 %
Input Crosstalk:	> 65dB @ 1KHz (Adjacent Channels)
S/N Ratio:	90dB single channel - fader max (A-weighted)
Dynamic Range:	90dB single channel - fader max (A-weighted)
Common Mode Rejection Ratio:	> 60dB @ 1 KHz
MIC Impedance:	3kΩ (XLR Balance);6.6kΩ (1/4)
MIC Gain:	0 to 45 dB (XLR)
Power Supply:	DC 5V (1A)
Dimensions(mm):	260 (L) ×230 (H) ×89 (D)
Weight:	1.5kg

Podcast⁺
Podcast Production Studio

Key Features

- MIC.Prior/Duking**
 - When the MIC PRIOR switch is turned on, it automatically reduces the volume of background music and sound effects when there is audio input from the microphone
- Intelligent Noise Reduction**
 - When the noise reduction switch is turned on, it reduces the ambient noise picked up by the microphone.
- Simulate On-site Reverberation**
 - Podcast+ has 16 simulated live reverb effects internally, which can be selected according to the live content to enhance the atmosphere of the live broadcast.
- Custom Sound Effects**
 - Comes with 9 built-in sound effects, which can be replaced via USB.
- 2 Headphone Outputs**
- High-pass Filter**
- 48V Phantom Power Supply**
- 2 Digital Audio Inputs/Outputs**
- 3 High-Quality Inputs**

