

EZD.B8

| WIRELESS BODYPACK
 TRANSMITTER



Description

- The EZD.B8 is a rugged and durable bodypack transmitter designed for reliable performance. Its compact and lightweight construction allows for comfortable waist-worn operation or discreet placement under clothing. Compatible with the EZD.Mi Series Digital Wireless Microphone System, it features a 3.5 mm microphone input for connecting Relacart LM-P01 lavalier microphones or HM-P06 headset microphones. It also provides a 3.5 mm line input for connecting an instrument output, allowing the microphone and line inputs to be used simultaneously.
- Powered by two AA batteries with an energy-efficient design, it delivers 8–10 hours of continuous operation. Suitable for diverse scenarios including home entertainment, personal performances, commercial events, and conference environments.

Product Specification

Carrier Frequency Range:	470MHz ~ 936MHz
Harmonic Radiation:	More than 45dB below carrier
Bandwidth:	128MHz (region-dependent)
Modulation:	D-QPSK
Audio Input:	3.5mm external microphone interface *1 ,3.5mm line input*1
RF Output Power:	+13dBm
Battery:	2×AA
Current Consumption:	150mA (typical)
Battery Life:	Approx. 12 hours (alkaline)
Dimensions (mm):	198 (H) × 52.5 (W) × 28 (D)